



**Automations- und
Steuerungstechnik GmbH**

EIB IR Artcase



**controlling TV, Video, Sat
and the complete EIB
with only one telepilot**

Order number EIB-IR-Artcase: E001-H022000



IMPORTANT-READ CAREFULLY:

This b+b End-User License Agreement ("EULA") is a legal agreement between you (either an individual or a single entity) and b+b Automations- und Steuerungstechnik GmbH, for the software product identified above, which includes computer software and may include associated media, printed materials, and "online" or electronic documentation ("SOFTWARE PRODUCT"). By installing, copying, or otherwise using the SOFTWARE PRODUCT, you agree to be bound by the terms of this EULA.

SOFTWARE PRODUCT LICENSE

1. COPYRIGHT TREATIES

The SOFTWARE PRODUCT is protected by copyright laws and international copyright treaties, as well as other intellectual property laws and treaties. The SOFTWARE PRODUCT is licensed, not sold.

2. GRANT OF LICENSE.

This EULA grants you the following rights:

- a. Software Product. b+b grants to you as an individual, a personal, nonexclusive license to make and use copies of the SOFTWARE for the sole purposes of using the SOFTWARE's functionality.
- b. Storage/Network Use. You may also store or install a copy of the SOFTWARE PRODUCT on a storage device, such as a network server, used only to install or run the SOFTWARE PRODUCT on your other computers over an internal network; however, you must acquire and dedicate a license for each separate computer on which the SOFTWARE PRODUCT is installed or run from the storage device. A license for the SOFTWARE PRODUCT may not be shared or used concurrently on different computers.
- c. Electronic Documents. Solely with respect to electronic documents included with the SOFTWARE PRODUCT, you may make an unlimited number of copies (either in hardcopy or electronic form), provided that such copies shall be used only for internal purposes and are not republished or distributed to any third party.

3. DESCRIPTION OF OTHER RIGHTS AND LIMITATIONS.

- a. Limitations on Reverse Engineering, Decompilation, and Disassembly. You may not reverse engineer, decompile, or disassemble the SOFTWARE PRODUCT.
- b. Separation of Components. The SOFTWARE PRODUCT is licensed as a single product. Its component parts may not be separated for use on more than one computer.
- c. Changing documentations. You may not make changes to the documentation of the SOFTWARE PRODUCT.
- d. Termination. Without prejudice to any other rights, b+b may terminate this EULA if you fail to comply with the terms and conditions of this EULA. In such event, you must destroy all copies of the SOFTWARE PRODUCT and all of its component parts.



4. COPYRIGHT.

All title and copyrights in and to the SOFTWARE PRODUCT (including but not limited to any images, photographs, animations, video, audio, music, text, and "applets" incorporated into the SOFTWARE PRODUCT), the accompanying printed materials, and any copies of the SOFTWARE PRODUCT are owned by b+b or its suppliers. The SOFTWARE PRODUCT is protected by copyright laws and international treaty provisions. Therefore, you must treat the SOFTWARE PRODUCT like any other copyrighted material except that you may install the SOFTWARE PRODUCT on a single computer provided you keep the original solely for backup or archival purposes. You may not copy the printed materials accompanying the SOFTWARE PRODUCT.

5. LIMITED WARRANTY

Except with respect to the REDISTRIBUTABLES, which are provided "as is," without warranty of any kind, b+b warrants that (a) the SOFTWARE PRODUCT will perform substantially in accordance with the accompanying written materials for a period of ninety (90) days from the date of receipt, and (b) any hardware accompanying the SOFTWARE PRODUCT will be free from defects in materials and workmanship under normal use and service for a period of one (1) year from the date of receipt.

6. CUSTOMER REMEDIES.

b+b's entire liability and your exclusive remedy shall be, either (a) return of the price paid, or (b) repair or replacement of the SOFTWARE PRODUCT or hardware that does not meet b+b Limited Warranty. This Limited Warranty is void if failure of the SOFTWARE PRODUCT or hardware has resulted from accident, abuse, or misapplication.

NO OTHER WARRANTIES: TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW, b+b DISCLAIMS ALL OTHER WARRANTIES

NO LIABILITY FOR CONSEQUENTIAL DAMAGES: TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW, IN NO EVENT SHALL b+b OR ITS SUPPLIERS BE LIABLE FOR ANY SPECIAL, INCIDENTAL, INDIRECT, OR CONSEQUENTIAL DAMAGES WHATSOEVER (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS OF BUSINESS PROFITS, BUSINESS INTERRUPTION, LOSS OF BUSINESS INFORMATION, OR ANY OTHER PECUNIARY LOSS) ARISING OUT OF THE USE OF OR INABILITY TO USE THE SOFTWARE OR HARDWARE PRODUCT, EVEN IF b+b HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Life support:

These products are not designed for use in life support appliances, devices or systems where malfunction of these products can reasonably be expected to result in personal injury. b+b customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify b+b for any damages resulting from such application.

Copyright 1998 - 2009 b+b Automations- und Steuerungstechnik GmbH. All rights reserved.



Automations- und Steuerungstechnik GmbH

Rev: 03/2009

EIB-IR-Artcase, the compact infra-red receiver for the EIB

4/11

Microsoft and Windows are trademarks of Microsoft Corporation.
Adobe, Adobe Type Manager is a trademark of Adobe Systems INC.
PaintBrush is a trademark of Z - Soft Corporation.

This handbook describes also functions, which are options.
Only qualified persons are allowed to install our units.

Softwaredesign und Coding:	Volker Knapp, Hartmut Zander, Peter Bernert
Documentation:	Volker Knapp, Peter Bernert
Editor:	Steffen Kiene

b+b Automations- und Steuerungstechnik GmbH
Eichenstraße 38a
D-64743 Beerfelden
Tel.: +49 6068 / 478910
Email: support@bb-steuerungstechnik.de
Internet: <http://www.bb-steuerungstechnik.de>



Contents

Highlights EIB-IR-Artcase.....	6
Fields of application.....	6
Contents of delivery.....	6
Introduction.....	7
Technical datas EIB-IR-Artcase.....	7
EIB-IR-Artcase view.....	8
EIB-IR-Artcase connectors.....	8
Technical datas EIB-IR-telepilot (not part of delivery).....	8
ETS Parametrization.....	9
Parametrization software for telepilot.....	10
Installation of IRGen.....	10
Using IRGen.....	10



Highlights EIB-IR-Artcase

- handles TV, Video, Sat and the complete EIB with one infra red remote control
- supports all EIB-telegrams up to 2 bytes (even non-EIS)
- supports switching, dimming, temperature adjust, shutters, central functions...
- graphic touch screen
- display of rooms, floors, buildings close to reality
- easy integration into existing EIB systems
- contains 1 IR-receiver with integrated EIB-bus-coupler
- no ETS required to parametrize the tele pilot

Fields of application

- Replacement of most of all tele pilots for consumer electronics and controlling the complete EIB
- Discrete controlling of light and more in conference rooms direct by the speaker
- Controlling EIB independent of fix mounted pushbuttons
- Replacement of control panels
- Replacement of arrays of pushbuttons
- Individual controlling of rooms with removeable walls

Contents of delivery

- 1 EIB IR sensor with integrated EIB-Buscoupler
- software
- 1 software for parametrization of EIB into Philips Pronto
- Documentation



Introduction

IR-EIB-Artcase requires a Philips Pronto tele pilot. This is a self-learning and programmable remote control with a touch-screen. It replaces nearly all tele pilots for consumer electronics like TV, SAT, Video with only one unit. One telepilot is usable to control all EIB actors. Switching, dimming, temperature adjustment and shutters. One IR-controller supports up to 8 IR-sensors.

In teach in mode, you can copy the complete functions of consumer telepilots used for TV-, Video- und SAT. Functions of most of all manufacturers are already integrated. So you can omit tech in. Just click to a device and import all functions.

Programming of EIB-functions is easily done by typing in the group address, EIS-Type and function.

See also: CCEIBSPS, EIB-Control-Platform, ActiveX, DLLs, OPC offer texts.

Technical datas EIB-IR-Artcase

Main voltage:	no external energy required
Fitting:	round, 110mm
Supported group addresses:	32767
Supported EIS-types:	all up to 2 bytes
Supported telepilots / IR-controller	unlimited



EIB-IR-Artcase view



EIB-IR-Artcase connectors

E1	EIB-programming LED
K1	EIB-program key for physical address
X1	EIB-connector
E2	EIB telegram LED
E3	IR receive LED (Infrared receiver)
E4	Supply LED (power supply)

Technical datas EIB-IR-telepilot (not part of delivery)

Operating interface:	Touchscreen
Display:	LCD, graphic, monochrome, backlite
Grayscale:	4
Power supply:	4 batteries LR6 AA 1,5V



Supported group addresses:	32767
Supported EIS-types:	all up to 2 bytes
Programing:	Teach in or by PC
PC connection:	serial, V24
IR distance:	up to 15m
Dimensions: (W*H*D)	92*35*140mm
Display dimensions:	79*60mm
Supported versions:	RU890, RU940 and RU970 (colour)



ETS Parametrization

The EIB-IR-controller needs only a physical address.

To select a physical address, just select a BCU1-bus coupler in the ETS (for example serial bus coupler or universal bus coupler for timers).



Parametrization software for telepilot

Part of delivery of the telepilot is the original parametrization software of the manufacturer. In addition, part of delivery is the software „IRGEN“ to parametrize the group addresses, EIS-types and values.

Installation of IRGen

1. Start the program prontoedit2_0.exe in the directory d:\eib ir fb\prontoedit\ (if „d“ is your CD-rom drive). Take attention to the instructions of the manufacturers installation program.
2. Copy prontoini.exe into the same directory as the ProntoEdit.
3. Start Prontoini.exe and set „developer mode“.
4. Copy the files "IRGEN.EXE", "IRGENKEY.DLL" and "IRGEN.INI" from d:\eib ir fb\irgen\ into the directory of ProntoEdit.

Options

If you want to use 2-step group addresses, set "GADual" in "IRGEN.INI" to "1". Use a standard text editor.

```
[SETTINGS]
```

```
GADual=1
```

Using IRGen

You have to enter the group address in the upper part of the window. In the next field you have to select the EIS type of the address. In the last input field you have to enter the value you want to write to the address. If you want the value to be written repeatedly until the user is releasing the button on the IR control, you have to enable the "telegram repetition" option.



For example:

If you want to write the value "1" to the binary address "0/0/1", you have to enter the following values:

Groupaddress: "0/0/1"
EIS type: "0010: Switch"
Value: "1"
Telegram rep.: "No"

After you have defined the desired telegram, simply press the "Create IR code" button. Now the ProntoEdit code will be displayed and automatically send to the clipboard as well.

Now you can use the ProntoEdit application to set the new code to a control button (double-clicking the button, etc.), if you are using the V2 version of the ProntoEdit software you can also try the automatic <F5> mode: move you mouse cursor over the ProntoEdit button, and hit the <F5> key. Now the IRGen software will try to do all necessary steps to enter the displayed IR code into the button properties.

After you have parametrized all the ProntoEdit buttons/controls you want to use, you can download your project to the remote control.