

SWITCHING WITH 1-CHANNEL OCCUPANCY DETECTOR AS MASTER VERSION

(MOTION DETECTOR FOR INSIDE USE)

LUXOMAT® PD4-M-1C-SM/-FC/-FM





























■ TECHNICAL DATA

230 V~ ±10 %



O 360° seated

Ø 6.40 m Ø 24.00 m

across towards

Ø 8.00 m IP20 / Class II / \in

IP 🗆

SM Ø 98 x H 65 mm FC Ø 97 x H 103 mm FM Ø 97 x H 84 mm

-25°C to +50°C

Housing UV- and shockresistant Polycarbonate

15 sec. - 30 min. or impulse

IR-PD, IR-PD-Mini


Channel 1 (Control the lighting)

2300 W, $\cos \varphi = 1$; 1150 VA, $\cos \varphi = 0.5$

10 - 2000 Lux

(i) PRODUCT INFORMATION

- Remote controllable occupancy detector for inside use LUXOMAT® PD4-M-1C as Master version for surface, false ceiling and flush mounting with circular detection area
- One channel to switch the lighting (potential free)
- Switching for all types of light fixtures by high performance relay
- Optical system, designed for highest
- The connection of a unlimited number of slaves for reasonable extension is possible!
- Serial impulse function
- Typical applications: monitoring of large areas like underground garages, gyms, warehouses, loading ramps, halls



- 1 Walking towards
- 2 Walking across
- 3 Seated activity

ACCESSORY (OPTIONAL)



separately)



IR-PD-Mini













Р	D	4	-S
•	_	•	-

Description	Colour	Part number
PD4-M-1C-SM	white	92580
PD4-M-1C-FC	white	92585
PD4-M-1C-FM	white	92575
Accessory (optional)		
Wire basket BSK	white	92199
LUXOMAT® IR-PD	grey	92160
LUXOMAT® IR-PD-Mini	grey	92159
Socket IP54 for PD4-SM	white	92161
Covering IP23	transparent	92206

